

USER MANUAL

NANLUX

INNOVATE · ILLUMINATE

Evoked 1200

DMX REFERENCE GUIDE

WWW.NANLUX.COM

CATALOG

DAYLIGHT 8bit	01	STORM	06
DAYLIGHT 16bit	01	TV	07
ULTIMATE DMX 8bit - DAYLIGHT MODE	02	PAPARAZZI	07
ULTIMATE DMX 8bit - EFFECT MODE	03	CANDLE/FIRE	08
DMX EFFECT CHART		BAD BULB	09
INT LOOP	04	FIREWORK	09
FLASH	05	EXPLOSION	10
PULSE	05	WELDING	11

DAYLIGHT 8bit

CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	DIMMER 0.0% to 100.0%	
2	0-127 128-255	0-50 51-100	FAN ON FAN OFF	

DAYLIGHT 16bit

CHANNEL	VALUE	%	FUNCTION	NOTES
1-2	0-65535	0-100	DIMMER 0.0% to 100.0%	
3	0-127 128-255	0-50 51-100	FAN ON FAN OFF	

ULTIMATE DMX 8bit - DAYLIGHT MODE

CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	DIMMER 0.0% to 100.0%	
2	0-63 64-127 128-255	0-25 26-50 51-100	MODE DAYLIGHT EFFECT RESERVED	0 ≤ value ≤ 63
3-9			N/A	
10	0-127 128-255	0-50 51-100	FAN ON FAN OFF	

ULTIMATE DMX 8bit - EFFECT MODE

CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	DIMMER 0.0% to 100.0%	
2	0-63 64-127 128-255	0-25 26-50 51-100	MODE DAYLIGHT EFFECT RESERVED	64 ≤ value ≤ 127
3	0-18 19-36 37-54 55-72 73-90 91-108 109-126 127-144 145-162 163-180 181-198 199-255	0-7 8-14 15-21 22-28 29-35 36-42 43-50 51-57 58-64 65-71 72-78 79-100	EFFECT MODE INT LOOP FLASH PULSE STORM TV PAPARAZZI CANDLE/FIRE BAD BULB FIREWORK EXPLOSION WELDING RESERVED	
4	0-255	0-100	DMX EFFECTS PARAMETER #1	See DMX Effects chart
5	0-255	0-100	DMX EFFECTS PARAMETER #2	See DMX Effects chart
6	0-255	0-100	DMX EFFECTS PARAMETER #3	See DMX Effects chart
7	0-255	0-100	DMX EFFECTS PARAMETER #4	See DMX Effects chart

ULTIMATE DMX 8bit - EFFECT MODE

CHANNEL	VALUE	%	FUNCTION	NOTES
8	0-255	0-100	DMX EFFECTS PARAMETER #5	See DMX Effects chart
9	0-255	0-100	DMX EFFECTS PARAMETER #6	See DMX Effects chart
10	0-127 128-255	0-50 51-100	FAN ON FAN OFF	

DMX EFFECT CHART

EFFECT	INT LOOP 0 ≤ value ≤ 18			
CH4/PARAMETER #1	DIM LOW			
CH5/PARAMETER #2	SPEED			
CH6/PARAMETER #3	CYCLE: ONE WAY = 0-85(0%-33%) CYCLE: TWO WAY = 86-170(34%-66%) CYCLE: REVERSE = 171-255(67%-100%)			
CH7/PARAMETER #4	ADD-ON: OFF = 0-63(0%-25%)	ADD-ON: FLASH = 64-127 (26%-50%)	ADD-ON: RANDOM FLASH = 128-191(51%-75%)	ADD-ON: PULSE = 192-255 (76%-100%)
CH8/PARAMETER #5	N/A	INTERVALS	SPEED	PULSES/MIN
CH9/PARAMETER #6	N/A	FLASH RATIO	N/A	N/A

DMX EFFECT CHART

EFFECT	FLASH 19 ≤ value ≤ 36	
CH4/PARAMETER #1	INTERVALS	
CH5/PARAMETER #2	FLASH RATIO	
CH6/PARAMETER #3	PAUSE: OFF = 0-127(0%-50%)	PAUSE: ON = 128-255(51%-100%)
CH7/PARAMETER #4	N/A	
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	

DMX EFFECT CHART

EFFECT	PULSE 37 ≤ value ≤ 54	
CH4/PARAMETER #1	PULSES/MIN	
CH5/PARAMETER #2	N/A	
CH6/PARAMETER #3	N/A	
CH7/PARAMETER #4	N/A	
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	

DMX EFFECT CHART

EFFECT	STORM 55 ≤ value ≤ 72	
CH4/PARAMETER #1	FLASH TIMES HIGH	
CH5/PARAMETER #2	FLASH TIMES LOW	
CH6/PARAMETER #3	TRIGGER: AUTO = 0-127(0%-50%)	TRIGGER: MANUAL = 128-255(51%-100%)
CH7/PARAMETER #4	INTERVAL HIGH	Trigger: OFF = 0-127(0%-50%) Trigger: ON = 128-255(51%-100%)
CH8/PARAMETER #5	INTERVAL LOW	N/A
CH9/PARAMETER #6	PAUSE: OFF = 0-127(0%-50%) PAUSE: ON = 128-255(51%-100%)	N/A

DMX EFFECT CHART

EFFECT	TV 73 ≤ value ≤ 90
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

DMX EFFECT CHART

EFFECT	PAPARAZZI 91 ≤ value ≤ 108
CH4/PARAMETER #1	SPEED
CH5/PARAMETER #2	N/A
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

DMX EFFECT CHART

EFFECT	CANDLE/FIRE 109 ≤ value ≤ 126
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	FLICKER: OFF = 0-127(0%-50%) FLICKER: ON = 128-255(51%-100%)
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

DMX EFFECT CHART

EFFECT	BAD BULB 127 ≤ value ≤ 144
CH4/PARAMETER #1	INTENSITY
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

DMX EFFECT CHART

EFFECT	FIREWORK 145 ≤ value ≤ 162
CH4/PARAMETER #1	SPEED
CH5/PARAMETER #2	DECAY
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

DMX EFFECT CHART

EFFECT	EXPLOSION 163 ≤ value ≤ 180	
CH4/PARAMETER #1	DECAY	
CH5/PARAMETER #2	TRIGGER: AUTO = 0-127(0%-50%)	TRIGGER: MANUAL = 128-255(51%-100%)
CH6/PARAMETER #3	SPEED	Trigger: OFF = 0-127(0%-50%) Trigger: ON = 128-255(51%-100%)
CH7/PARAMETER #4	N/A	
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	

DMX EFFECT CHART

EFFECT	WELDING 181 ≤ value ≤ 198
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	PAUSE: OFF = 0-127(0%-50%) PAUSE: ON = 128-255(51%-100%)
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

Version: V2 2021-11-03

 +86-754-85751187

 +86-754-85300887

 info@nanlux.com

 Zhanglin,324,Dongli Chenghai Shantou Guangdong China

Guangdong NanGuang Photo&Video Systems Co., Ltd