

## 4-Battery Power Station Box

### S-4010/S-4020/S-4030

- ◆ Install 4x V-mount batteries
- ◆ 2x XLR DC output (12V or 24V option)
- ◆ Real time output voltage LED display
- ◆ Low battery warning
- ◆ Charging without take out batteries
- ◆ Intelligent protective circuit design
- ◆ PP + Fiber glass case, strong and durable



### Output Descriptions:

	<b>S-4010</b> 12v + 12v <b>Dual 12V output</b>	4-pin XLR 11-16.8V DC output x2 Max Load: 15A/180W per channel 2 channels output simultaneously
	<b>S-4020</b> 12v + 24v <b>12V + 24V output</b>	4-pin XLR 11-16.8V DC output x1 Max Load: 15A/180W 3-pin XLR 22-33.6V DC output x1 Max Load: 15A/360W 12V and 24V will not output simultaneously
	<b>S-4030</b> 24v + 24v <b>Dual 24V output</b>	3-pin XLR 22-33.6V DC output x2 Max Load: 15A/360W in total 2 channels output simultaneously

### Specification

Model	S-4010	S-4020	S-4030
Input	DC 16.8V 5A (Charging)	DC 16.8V 5A (Charging)	DC 16.8V 5A (Charging)
Output	DC11-16.8V 15Ax2 (180Wx2)	DC 11-16.8V 15A (180W) Or DC 22-33.6V 15A (360W)	DC 22-33.6V x2 Total 15A(360W)
Dimension	290mm x 221mm x 278mm		
Net weight	3.45Kg		
Working environment	Working temperature: 0°C ~ +40°C Working humidity: 10% ~ 90% Storage temperature: -15°C ~ + 60°C		